

In-Wall **PREMIUM BT** & In-Wall **FM/DAB** Display



eISSOUND

Electrónica Integral de Sonido S.A. declares that the equipment ref.328x1, 328x2, 527x7 and 527x6 is in accordance with directives 2014/53/UE, 2011/65/UE, 2009/125/EC. The EU declaration of conformity can be requested through the website www.eissound.com


CC-1205ENG-02
64460133

1. Description

In-Wall PREMIUM BT & In-Wall FM/DAB Display is a standalone audio module. It allows you to enjoy four audio channels: Bluetooth Audio, FM/DAB Radio and TWO stereo or four mono audio inputs. Although it is ideal as a standalone FM/DAB radio option (Ref. 328x1, 328x2) the PREMIUM BT version (Ref. 527x7, 527x6) that includes Bluetooth Audio, make it the perfect audio system.

2. Installation

2.1 BASIC INSTALLATION




Note: It is two stereo channels from two external stereo audio sources.

2.2 TECHNICAL SPECIFICATIONS

328x1 / 328x2 / 527x6 / 527x7	MIN	NORMAL	MAX		COMMENTS
Measurements		45x45x45,5		mm	exterior (width x height x depth)
		45x45x36		mm	cavity (width x height x depth)
		45x45		mm	face cover (width x height)
Voltage		15	15,5	Vdc	terminals 2,4
Consumption demand 328x1, 527x7	8	50,2		mA	terminals 2,4
Consumption demand 328x2, 527x6	21	61		mA	terminals 2,4
Input signal		2,75		Vrms	terminals 15, 16, 25, 26, NORMAL mode
		1,22		Vrms	terminals 15, 16, 25, 26, PROF mode
		0,32		Vrms	terminals 15, 16, 25, 26, OTHER mode
Input impedance		3300		ohms	terminals 15
		33000		ohms	terminals 16, 25, 26
Audio output signal			1,5	W	terminals 05, 06, 04, 8 OHM mode
			1	W	terminals 05, 06, 04, 16 OHM mode
			1,288	Vrms	terminals 05, 06, 04, LINE mode
			2,585	Vrms	terminals 05, 06, 04, AMP1 mode
			1,82	Vrms	terminals 05, 06, 04, AMP2 mode
External amplifier activation signal			5	Vdc	terminals 05 (DC component)
			14	Vdc	terminal 0/62
Call reception signal		2,75		Vrms	terminal 7
Passband	20		22000	Hz	
Distortion		0,1	1	%	
Frequency range	87,5		108	MHz	FM
	174		240	MHz	DAB
Antenna impedance		75		ohms	FM
		50		ohms	DAB
Antenna sensitivity		3,5	10	uV	
Tuner distortion			1	%	
Number of memories FM			10		
Number of memories DAB			10		
Bluetooth spec.	Class2 BT4.2 dual mode BLE, A2DP 1.3, AVRCP 1.6C				Only 527x6, 527x7 models
Wireless transceiver		2,4		GHz	ISM Band, only 527x6, 527x7 models
RF transmission power		2		dBm	Only 527x6, 527x7 models
RF antenna		internal			Only 527x6, 527x7 models
Bluetooth range			10	m	Only 527x6, 527x7 models

TERMINALS




FM / DAB ANTENNA

For FM installations connect a 75cm wire to the antenna terminal (A). For DAB installations: connect a 31cm wire to the antenna terminal (A). Be sure to locate it as far as possible from any sources of electrical noise such as halogen lamps, HVAC, fluorescent bulbs, etc. and as far as possible of the other installation wires.

To improve the FM and DAB reception it is advisable to use a 75/50 ohm antenna amplified instead of the antenna wire.

For DAB, WE STRONGLY RECOMMEND TO CONNECT A DAB AERIAL.



2.3 INSTALLATION MENU

When accessing the Installation menu please take note that the Module Control Unit must be in OFF mode.

To activate the installation menu press the **v** and **+** keys simultaneously for 6".



1. Use the **v** and **^** key to scroll through the menu.
2. Use **+** and **-** keys to scroll up and down through the options.
3. Only use the **CH** key to validate the option selected.

LANGUAGE:

Select the language desired for the display.

AUTO ON/OFF: By default the Control Unit starts in OFF status when it is powered (2,4 terminals). Activating the AUTO ON option the Control Unit will start in ON status (IDEAL mode) when powered.

MONO / STEREO: Selects the Control Unit's audio output mode (terminals 04, 05, 06) between MONO or STEREO.

AUDIO OUTPUT: Adjusts the audio output level of the Control Unit (terminals 04, 05, 06) between 8 OHM, 16 OHM, LINE (line level), AMP1 (output for EISSOUND amplifiers ref. 13102 and 13203), and AMP2 (output for EISSOUND amplifier ref. 13204).

BALANCE: Adjusts the left / right balance of the audio output (terminals 04, 05, 06).

VOL LIMIT: Limits the maximum volume for the user.

MENU LOCK: Locks / unlocks access to the user menu and the FM/DAB save/delete memories' menu.

INSTALLATION MENU	I N S T
	E N G E S P F R A G E R
LANGUAGE	
	A U T O N A U T O F F
AUTO ON / OFF	
	S T E R E O M O N O
MONO / STEREO	
	8 O H M 1 6 O H M L I N E A M P 1 A M P 2
AUDIO OUTPUT	
	B A L - 1 5 B A L + 1 5
BALANCE	
	M A X 0 0 M A X 9 9
VOLUME LIMIT	
	L O C K U N L O C K
MENU LOCK	

L1 ENABLE: Activates / deactivates the input channel L1 (terminals 15, 16). When L1 is disabled, it will not appear when selecting the audio channels with the CH key.

L2 ENABLE: Activates / deactivates the input channel L2 (terminals 25, 26). When L2 is disabled, it will not appear when selecting the audio channels with the CH key.

FM ENABLE: Activates/deactivates the FM audio channel. When FM is disabled it will not appear when selecting the audio channels with the CH key.

L1 MONO / STEREO / MIX: In STEREO mode (default mode) the terminals 15 and 16 will be a left and right STEREO input. To activate this option, press the CH key, the display will show L-IN 1 (label that can be customized with the L1 LABEL menu option).

In MONO mode the terminals 15 and 16 will be two independent MONO channel inputs. To activate these two channels press CH key, the display will show L-IN 11 (input on terminal 15) and L-IN 12 (input on terminal 16).

In MIX mode the terminals 15 and 16 will be two independent MONO channel inputs and to listen to both channels mixed press the CH key and the display will show MIX1. (See diagrams in Annex 1).

L2 MONO / STEREO / MIX: In STEREO mode (default mode) the terminals 25 and 26 will be a left and right STEREO input. To activate press the CH key and the display will show L-IN 2 (label that can be customized with the menu option L2 LABEL).

In MONO mode the terminals 25 and 26 will be two independent MONO channel inputs. To activate these two channels press the CH key and the display will show L-IN 21 (input on terminal 25) and L-IN 22 (input on terminal 26).

In MIX mode the terminals 25 and 26 will be two independent MONO channel inputs and to listen to both channels mixed press CH key and the display will show MIX2. (See diagrams in Annex 1).

L1 ENABLE	L 1	0 N
	L 1	0 F F
L2 ENABLE	L 2	0 N
	L 2	0 F F
FM ENABLE	F M	0 N
	F M	0 F F
L1 MONO / STEREO	L 1	M 0 N
	L 1	S T
	L 1	M I X
L2 MONO / STEREO	L 2	M 0 N
	L 2	S T
	L 2	M I X

L1 INPUT LEVEL: Adjust the audio input level of the L1 channel (terminals 15, 16) between the options NORMAL (100 series), PROF (professional) or OTHER (Euroconnector level).

L2 INPUT LEVEL: Adjust the audio input level of the L2 channel (terminals 25, 26) between the options NORMAL (100 series), PROF (professional) or OTHER (Euroconnector level).

L1 LABEL: Set the identification label of the audio source connected to the L1 channel (terminals 15, 16) between the options: L-IN 1 (default), BT (Bluetooth), TV, FM-CEN (100 series central FM tuner). The customization of this tag is available only when the L1 channel is set up as STEREO.

L2 LABEL: Set the identification label of the audio source connected to the L2 channel (terminals 25, 26) between the options: L-IN 2 (default), BT (Bluetooth), TV, FM-CEN (100 series central FM tuner). The customization of this tag is available only when the L2 channel is set up as STEREO.

FM CENTRAL: Allows connection with our 100 series central FM tuner to the input L1 (terminals 15,16) or L2 (terminals 25,26).

TERMINAL 0: Allows connection with terminal 0/62 to the terminal 0 of 100 series FM tuner or to the terminal 62 of the ceiling amplifier ref. 13204.

FACTORY RESET: Press the CH key to activate the factory reset.

VERSION: Press the CH key to check the Control Unit version.

L1 INPUT LEVEL	N O R M A L P R O F O T H E R
L2 INPUT LEVEL	N O R M A L P R O F O T H E R
L1 LABEL	L - I N 1 B T T V F M - C E N
L2 LABEL	L - I N 2 B T T V F M - C E N
FM CENTRAL	L - I N 1 L - I N 2
TERMINAL 0	C E N T R L R A P
FACTORY RESET	R E S E T
VERSION	V E R S

3. User Menu

When accessing the user menu, please take note that the Module Control Unit must be in OFF mode.

To activate the User Menu press the **v** key for 3".

1. Use the **v** and **^** key to scroll through the menu.
2. Use **+** and **-** keys to scroll up and down through the options.
3. Only use the **CH** key to validate the option selected.



FM MEMORY DELETE: Delete all FM favorites stored in the memory.

FM FORCED MONO: Activates / deactivates FM reception in MONO. Recommended when the reception is weak.

FM SENSITIVITY: Option to adjust the automatic station seek sensitivity for the Control Unit.

DO NOT DISTURB: In use only when connected to our 100 series audio system. Activates the "do not disturb" mode to avoid receiving calls. The NO CALL symbol appears on the display.

CALL VOL: In use only when connected to our 100 series audio system. Adjusts the volume level of the call message reception.

LIGHT ON: Adjusts the brightness level of the display when the Control Unit is in the ON status.

DAB SERVICES SCAN: Search and update the list of receivable DAB services.

Note: the first time the DAB audio channel is selected with the CH key, the Unit does not

USER MENU	U S E R
FM MEM. DELETE	D E L
FM FORCED MONO	S T E R E O M O N O
FM SENSITIVITY	S E N S 1 S E N S 2 S E N S 3
DO NOT DISTURB	N O C A L L C A L L
CALL VOLUME	C A L L 0 0 C A L L 9 9
LIGHT ON	L O N 1 L O N 5
DAB SERVICES SCAN	D R B


have any service available so it will start the scan automatically. If no services are found, the display will show NO AVAILABLE SERVICES. The DAB SERVICES SCAN can be updated, at any time, by pressing the CH key using the User Menu option.

DAB MEMORY DELETE: To delete all DAB favourites stored press the CH key.

DAB MEMORY DELETE

D E L

4. Operation



4.1 FM MANUAL SCAN

To select the FM stations press the **CH** key to select the FM audio channel. With the **▲** and **▼** keys make a long press to scan through the FM stations (See also “Fine Tuning”).

4.2 DAB SERVICES

When choosing the DAB channel the DAB option will scan automatically all DAB stations available.

With the **▲** and **▼** keys make a long press to scan through the DAB stations.

4.3 FM/DAB MEMORY PROGRAM

Pressing simultaneously the **▲** and **+** keys for 3" the FM/DAB station selected is stored into the favourite memory list (max 10 memories). With a short press on the **▲** and **▼** keys you can scroll through the memories stored.



4.4 FM/DAB MEMORY DELETE

Pressing simultaneously the **▼** and **-** keys for 3" deletes from the favourite memory list the FM/DAB station selected.



4.5 FM FINE TUNING

Pressing the **CH** and **+** keys simultaneously for 3" set up the fine tuning options. The fine tuning options are as follows:

1. Short presses on **+** or **-** keys will search radio frequencies in steps from 50kHz to 50kHz.
2. Maintaining a long press on the **+** or **-** keys will rapidly search, without interruption, the frequency you desire.



4.6 BLUETOOTH

To select the Bluetooth option (PREMIUM BT references: 527x7 and 527x6), press the CH key and select the "BT" channel. Before pairing with your Bluetooth device check the ID and password by pressing the ▲ key for 3" for the ID and the ▼ key 3" for the password.

1. Open iOS/Android Bluetooth Settings Menu.
2. Select the ID of the PREMIUM BT which you wish to pair (e.g. 1221 PREMIUM BT).
3. Introduce the password (e.g. 8712). Needed only when pairing, not in future connections.
4. Check that the PREMIUM BT (e.g. 1221 PREMIUM BT) is correctly connected.

Bluetooth ID



Bluetooth password



IOS:



ANDROID:



5. Keyboard Shortcuts



EQUALIZATION:

Pressing the **CH** key for 3" allows you to select with the **▲** and **▼** keys a pre-equalization mode among the 12 available.



TIMER:

Pressing the **ON / OFF** key for 3" allows you to set an elapsed time with the **+** and **-** keys by which the Control Unit will automatically switch to standby.



SET IDEAL:

Press simultaneously the **+** and **-** keys to activate the ideal mode previously saved.



SAVE IDEAL:

Pressing simultaneously the **+** and **-** keys for 3" will save the ideal mode in memory (volume, equalization, audio channel and station, if the channel is FM) selected previously.



AUDIO CHANNEL = BLUETOOTH

BLUETOOTH ID:

Press the **▲** key for 3" to search for the PREMIUM BT ID.



AUDIO CHANNEL = BLUETOOTH

BLUETOOTH PASSWORD:

Press the **▼** key for 3" to search for the PREMIUM BT password.



AUDIO CHANNEL = FM

FM FINE TUNING:

Pressing the **CH** and **+** keys simultaneously for 3" you can set up the fine tuning options.



AUDIO CHANNEL = FM

FM FORCED MONO:

Pressing the **CH** and **▲** keys simultaneously for 3" allows you to activate/deactivate the MONO mode.



AUDIO CHANNEL = FM/DAB

FM/DAB FAVORITES PROGRAM:

Pressing the **▲** y **+** keys simultaneously for 3" allows you to save the selected station in favorites.



AUDIO CHANNEL = FM/DAB

FM/DAB FAVORITES DELETE:

Pressing the **▼** and **-** keys simultaneously for 3" allows you to delete the selected station from favorites.



CONTROL UNIT = OFF

USER MENU:

With the Module in OFF mode press the **▼** key for 3" to access to the user menu.




CONTROL UNIT = OFF

INSTALLATION MENU:

With the module in OFF mode press the **▼** key and **+** simultaneously for 6" to access to the installation menu.

6. Wiring diagrams

6.1 In-Wall PREMIUM BT / In-Wall FM/DAB Display + Amplifier (Ref.13204)




Note: It is four MONO channels from four external MONO audio sources.

7. Annex 1

L1 = STEREO


Stereo audio input L1



stereo audio input = channel L1

L1 = MONO


Two independent audio inputs:
L11 and L12



mono audio input = channel L11
mono audio input = channel L12

L1 = MIX


Two independent audio inputs
(L11 and L12) mixed at the output



mono audio input = channel L11
mono audio input = channel L12

L2 = STEREO


Stereo audio input L2



stereo audio input = channel L2

L2 = MONO


Two independent audio inputs:
L21 and L22



mono audio input = channel L21
mono audio input = channel L22

L2 = MIX

Two independent audio inputs
(L21 and L22) mixed at the output



mono audio input = channel L21
mono audio input = channel L22

eISSOUND

Pol. Malpica - Grupo Quejido 87-88
50016 Zaragoza - SPAIN
Tel. +34 976 46 55 50 Fax +34 976 46 55 59
marketing@eissound.com
www.eissound.com

KBSOUND

6550 St. Augustine rd. Av. Suite 305
Jacksonville, Florida 32217
info@kbsound.com
www.kbsound.com

