CBA[®]

Wireless Alert System

RA-4961-K1Q Wireless Receiver and Wireless Pushbutton

The RA-4961-K1Q Wireless Alert System can be synced with a wide variety of wireless devices to suit almost any situation.

Kit Includes:

- Wireless Receiver (RA-4961Q)
- Wireless Pushbutton (RA-4961-PBQ)

Features:

- Up to 1,000ft (305m) transmission range*
- Uses 914.8 MHz Frequency for less interference
- Audible (volume adjustable) and visual alert via built-in speaker and flashing light
- 18 programmable ringtones for each accessory
- Connect up to 4 wireless transmitter accessories
- Each channel independently programmable
- Output terminals for optional auxiliary device
- Low battery LED indicators on receiver unit for receiver and connected sensors
- Wall or desktop mountable



RA-4961Q shown

RA-4961-PBQ shown

Optional Accessories:

- Wireless Outdoor PIR Sensor (RA-4961-DSQ)
- Wireless Magnetic Contact (RA-4961-MCQ)
- Wireless Vibrating Receiver (RA-4961-VPQ)

| Model | RA-4961-PBQ Pushbutton |
|------------------------|--|
| Frequency | 914.8MHz |
| Transmission range* | Up to 1,000ft (305m) |
| Channels | 1 |
| Power supply | CR2032 Battery (included) |
| Estimated battery life | 400 days (3 triggers/day) |
| Low battery indicator | Zone LED on receiver blinks |
| | continuously |
| IP rating | IP45 |
| Operating temperature | -4°~140°F (-20°~60°C) |
| Dimensions | 1 ⁵ /16"x ¹¹ /16"x ³⁷ /16" (34x18x87mm) |

*Line of sight. Transmission range will vary depending on installation and operating environment.

Copyright 2021 © SECO-LARM U.S.A., Inc. All rights reserved. All trademarks are the property of SECO-LARM U.S.A., Inc. All rights reserved. The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

Specifications:

| Model | RA-4961Q Receiver |
|----------------------------------|---|
| Frequency | 914.8MHz |
| Channels | 4 |
| Accessories per channel | 1 |
| Relay output (Channel 4 only) | 1(Form C Relay), 1A@50VDC |
| Power Supply | 3 "C" batteries (not included) or 6VDC power adapter (X-HKP06-06005 - not included) |
| Estimated battery life | 270 days (3 triggers/day) |
| Low battery indicator | Notification LED flashes every 5 seconds |
| Accessory low battery | Zone LED for accessory blinks |
| indicator | continuously |
| Sound level (dB) | Up to 96dB@1ft(30cm) |
| Operating temperature | 32°~140°F (0°~60°C) |
| Dimensions | 5 ¹ /4"x1 ⁹ /16"x6 ⁵ /8" (133x40x169mm) |

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606 **Phone:** (949) 261-2999 | (800) 662-0800 **Fax:** (949) 261-7326 **Website:** www.seco-larm.com **Email:** sales@seco-larm.com

SECO-LARM[®] **ENFORCER[®]** CRIMEBUSTER[®] CBA **SLI**

PI_RA-4961-K1Q_210406.docx