

Multisensor 6

Z-Wave 5-in-1 Sensor: Motion, humidity, temperature, light, vibration sensor.





Motion sensor. Humidity sensor. Thermometer. Light sensor (including UV sensor). Vibration sensor.

Never before has one device so delicately-made. Never before has it provided you all-around protection. Multisensor 6 interprets smart in a brand-new perspective which will always furnish you a cozy and safe home.

The Aeon Labs MultiSensor 6 is a battery or DC powered (USB port), 5-in-1 Z-Wave sensor. It comes with a bracket to be installed on desktop, on the wall, and inside the ceiling.

Product highlights.

- 5-in-l sensor: Motion, humidity, temperature, light (including UV sensor), vibration sensor.
- Support battery power and DC input power. Battery: DC 5V 500mA, 2 x CR123A battery, which can let products work 2 years.
- Use Z-Wave 500 series chip.
- Optimized antenna range 300ft Z-Wave RF range (outdoor), 80+ ft (indoor).
- Certified/Available for ÙSA, ÉU and Australian markets (ETL, CE, RCM, FCC-ID, CCC,Z-Wave+).

Technical Specification.

- Motion Sensor: 5 meters, and 120 degree.
 Humidity Sensor: 20% to 95%, accuracy: +/- 5% at 25°C.
- Temperature Sensor: -10°C ~ 60°C, accuracy: +/- 0.5°C.
- Light Sensor: 0 lux to 1000lux.
- Vibration Sensor: act as tamper switch, ON or OFF.

Product Specification.

- Operation Temperature(Top): -20°C ~ 40°C
- Store Temperature: -40°C ~ 80°C
- Working Humidity: 8% ~ 80%
- Operational site: Indoor and outdoor