

## AS-6111Q Motion Entry Alert

A simple to install audible motion alert for indoor use—no need for any wiring. The sensor is perfect as a door annunciator or for monitoring passageways in a wide range of home, office, and commercial applications.

### Features:

- Mount next to a door or other entry point to alert when someone enters or exits
- Provides an audible alert (doorbell sound) when triggered
- Sounds for approximately 4 seconds or for as long as the sensor detects changes in visible light
- CDS sensor operates by detecting sudden changes in visible light\*
- Sensor range 10ft (3m)
- Battery operated (3 AAA batteries, not included)
- Designed for motion alerts only
- Low current drain (0.05mA standby)



### Specifications:

Power	1.5VDC AAA batteries x3 (not included)	
Current	Standby	Under 0.05mA@4.5VDC
	Active	Under 85mA@4.5VDC
Low battery indicators	Device will repeatedly activate	
Input signal	CDS sensor	
Output signal	Doorbell sound	
Sensor range	10ft (3m) at 20"~40" (0.5~1m) height	
Material	ABS plastic, white	
Dimensions (with bracket)	3 <sup>3</sup> / <sub>8</sub> "x3 <sup>3</sup> / <sub>8</sub> "x2" (85x85x50mm)	
Weight	3-oz (84g)	

**\*IMPORTANT:** AS-6111Q is designed to detect changes in visible light. Not for use in total darkness or facing a strong light.

### Additional Products:



Wireless Alert System  
RA-4961-K1Q



Full line of accessories for  
RA-4961-K1Q



Auto Voice Reminder  
AS-1511



Motion Entry Alert  
AS-6111Q